Allied Telesis Cable Box Update

- From the remote:
- Press the MENU button.
- Use the channel up/down button on the remote to scroll down to the Magnifying Glass. (see Fig. A) press OK.
- Press the channel up/down button to select S/W
 Upgrade by OTA and press OK.
- ***(Cont on Next Slide)





Allied Telesis Cable Box Update

Cont:

- Validate the setting shown in Fig. B.
 - Frequency = 270
 - Symbol Rate = 5057
 - Mode = **64-QAMB**
 - Download PID = 1998
- Press channel up/down to select START press
 OK.
- Box will begin to collect information and download
- (If the box does not start to collect information within 30 secs, select STOP and EXIT and reselect START)
- After the update completes, it will do a BurnFlash. Once the box has finished running Burnflash, it will reboot.
- After the box finishes rebooting, turn it OFF using the ON/OFF switch on the back of the box.
- Wait a few seconds and then turn box back ON and verify your channels.



